

Agri battery or mains - 20km

AE-A020J

The Agri. 20km energizers can be powered with a battery or by mains, making them handy and adaptable depending on your needs.



Features:

- Powers up to 20km of fence/32 acres/12.8ha (optimal conditions)
- Robust weather resistant system
- Battery charge state indicator
- Energizer overload indicator
- Day/night sensor
- Powered by battery or mains power adaptor
- Adaptable mounting options (wall, fence wire or wooden post)
- Lightning protection
- Many programmable options via the LCD handheld remote – (optional accessory) including adjustment of fence voltage and pulse rate, independent day/night setting, battery voltage reporting and fence performance monitoring

Specifications:

Output energy max 2J (stored energy 3.3J)
Output voltage open circuit 9.0kV
Output voltage @1000Ohms 6.5kV
Output voltage @500Ohms 6.0kV
Power source: Battery 12Vdc, Power supply 12Vdc
IP rating 54
Dimensions: H190 X W115 XD76mm