



## Equine battery or mains - 20km

### AE-A/EQ

The Equine 20km energizers can be powered with a battery or by mains, making them handy and adaptable depending on your needs. There are any programmable options via the LCD handheld remote, including adjustment of fence voltage and pulse rate, independent day/night setting, battery voltage reporting and fence performance monitoring



#### Features:

- Powers up to 20km of fence/32 acres/12.8ha (optimal conditions)
- Robust weather resistant system
- Battery charge state indicator
- Energizer overload indicator
- Day/night sensor
- Powered by battery or mains power adaptor (both sold separately)
- Adaptable mounting options (wall, fence wire or wooden post)
- Lightning protection

#### Specifications:

Output energy max 2J (stored energy 3.3J)  
Output voltage open circuit 9.0kV  
Output voltage @1000Ohms 6.5kV  
Output voltage @500Ohms 6.0kV  
Power source: Battery 12Vdc, Power supply 12Vdc  
IP rating 54  
Dimensions: H190 X W115 XD76mm