

KEYPAD

WIRELESS ACCESS CONTROL



Compatible
microSD

Applications

- Gate access control
- Garage door access control
- Striker lock access control
- Internal door mag-lock access control
- Arming / Disarming Alarms
- Wireless Doorbell

Specification:

Battery supply voltage	2 x AA Alkaline batteries (voltage range: 2.4V - 3.3V)
External power input	10V-14V DC input
Wireless range	30m indoors
Operating temperature	-10°C to +55°C
Operating humidity	0 - 90%
Outputs	9 Channels + 1 Doorbell output
Housing material	ABS Black
Rating	IP55
Battery life	2-3 years dependant on Usage
Usage life	60 000 activations
Code length	1 - 10 digits
Memory capacity	1000 unique codes

Certifications:

ETSI EN300 220-V2.4.1
ETSI EN301-489-3 V1.4.1
ETSI EN301-489-1 V1.9.2
IEC 60950-1:2005 + A1:2009
ICASA TA-2017/1846



Order Code

Keypad unit (wireless RF)	KEYPAD
AA Alkaline battery 1.5V	AA

The Sherlo Wireless Keypad is designed for Secure access control of buildings, properties, gate/garage entrances, internal doors, striker locks and even arming/disarming alarm panels. The unit can be programmed with up to 9 RF Channels to control different receivers. You can very easily program the keypad on a PC in Notepad so that you don't have to waste time manually programming the keypad. This can then be very easily & reliably saved onto the Keypad using a microSD card. The keypad is battery powered, but has a 12V DC wired input connector.

Features

- Wireless
- 1000 unique Pin code from 1-10 digit
- Backing up the unit with a microSD card
- Wrong code lock out function
- Holiday mode
- 9 Channel RF outputs
- 1 Door bell RF output
- Waterproof housing