

CCTV-TV2GASE

CONVERTER COMPOSITE TV TO VGA (ECON)



KEY FEATURES

- Easy plug for play
- Support Video and S-Video input
- Also support VGA input
- Switch function between of VGA,S-video, Video
- With image freezing function
- Auto adapt to the NTSC,PAL format
- Good quality of the clear image converter
- Auto saving when off power

TECHNICAL SPECIFICATIONS

1	Support (S-VIDEO、CVBS、VGA) signal input
2	Let Video signal converter to digital of VGA output
3	Support full screen horizontal scanner, horizontal /vertical image location, horizontal /vertical image adjust
4	Resolution : 800X600@60Hz — 1920X1200@60Hz
5	Auto adapt to NTSC PAL format, switch the Video and VGA signal
6	Support image brightness、contrast ratio、Color saturation, and freezing function
7	Output: Composite VGA
8	Power : DC 5V 1A

ACCESSORIES

NAME	QTY
BNC TO VGA converter	1
DC 5V power adaper	1
Video cable	1
Maunal	1

1. AV/SV : Switch between Video and S-video ;
2. ZOOM : image zoon ;
3. PIP : VGA output monitor of Picture in Picture function.
4. MODE : control output signal mode
5. MENU : Control the brightness, contrast ratio, colour saturation, language and so on. When you press PIP button at same time can to change parameter button
6. P.P : Control output VGA resolution adjust

INTERFACE CONNECTOR

NUMBER	FUNCTION
1	VGA INPUT
2	Video input
3	S-video input
4	VGA output
5	Power adapter
6	LED

