

Code Hopping Receiver

The **SENTRY CODE HOPPING Receiver** is a matching receiver to transmitter module offered in either one, two or three channel versions, standard or long range. It is capable of learning **SENTRY Code Hopping** & some other manufactured code hopping remote controls.



MERX2-C2



MERX1-C1



MERX1K-C/S



MERX3-C3

SPECIFICATIONS:

Power Source: 12-24VDC or 12-20VAC

Frequency: 403.55MHz / 433.92MHz

Physical Size: 90 x 66.5 x 30mm

Weight: 95g

Storage Temp: -10°C to +55°C

Operating Temp: 0°C to 40°C

Operating Humidity: <80%