

Binary Transmitters

The **SENTRY Binary remote control** is a compact, handheld remote control operating in the 403MHz or 433MHz band. The transmission code is set by means of the internal dipswitch up to 4096 unique combinations.



METX1-B1



METX3-B3



METX3-B3/433



METX1-B1/433

SPECIFICATIONS:

Power Source: Internal 12V
Battery (Type 23A)
Frequency: 403.55 / 433.92MHz
Transmission power: 350mW
Current consumption: 9mA active
Physical Size: 65 x 32 x 14mm
Weight: 30g
Storage Temp: -10°C to +55°C
Operating Temp: 0°C to 40°C
Operating Humidity: <80%

NOTE:

403.55MHz Is not sold outside southern Africa.
433.92MHz Is sold in black casings outside southern Africa.