

# **Code-Hopping Panic Remote**

## **Applications**

Frail care facilities nurse call
Panic activation for shop keepers
Response officer panic button
Home panic button

#### **Features**

Big button designed for elderly & frail people Moisture proof design

Unique antenna design incorporating the pendant chain to increase range by 50%

12V battery operation (23A Alkaline battery)

LED flashes when there is a low battery condition



## **Order Codes**

1 Button Pendant Remote	PTX1
Wall Mount bracket	WM
Replacement battery (23AE)	GP23A

### **Specification:**

Encryption:	Code-Hopping
Range:	500m (Open air)
Frequency:	403MHz
Voltage Range:	10V to 13V DC
Current draw:	32mA
Dimensions(lxbxh):	70 x 37 x 18mm
Gross Weight:	31 grams
Operating Temp:	-7°C to 65°C
Warranty:	24 Months

