

PASSIVE iR TRANSMITTER



Applications

Transmission of battery powered PIR's
Transmission of magnetic door contacts
Emergency break glass boxes
Roller shutter door contacts

Features

Alarm and Tamper transmit outputs (2 Channels)

Powered by 2 x Low cost AA Alkaline batteries

Battery life under normal conditions 3 years or
150 000 triggers

Selectable options for:-

- 120second Sleep mode on/off
- Normally Open or Normally Closed

Specification:

Encryption:	Code-Hopping
Range:	500m (Open air)
Frequency:	403MHz
Voltage Range:	2.2V to 4.5V DC
Current on TX:	+/-14mA
Sleep mode:	+/-400nano A
Dimensions:(lxbxh)	71x31x28mm
Gross Weight:	74 grams
Operating Temp:	-3°C to 65°C
Warranty:	24 Months

The new improved model is easier to install
& has up to 3 times longer battery life and a
120 second sleep mode function

Order Code

PIR Transmitter + 2x AA batteries	PIR_TX.V2
AA Alkaline battery 1.5V	AA