



Professional Black and White Laser Printer

Designed to deliver professional performance with flexible connectivity options and super-fast, high quality printing you can rely on.

The super high-yield inbox toner means you can print for longer whilst considerably reducing your spend. This, together with the robust build quality and flexible paper handling options, makes the HL-L6410DN the ideal print partner for your business.

HL-L6410DN





Key Features

- Print up to 50 pages per minute
- 2-Sided print, up to 24 sides per minute
- 8.9cm Colour LCD touchscreen
- Gigabit ethernet, optional 2.4GHz WiFi
- 1GB Internal memory with optional secure USB storage
- 520 sheet paper input tray expandable up to 1,560¹¹
- Comes with 25,000 page yield toner, 25,000 maximum yield available⁷
- Compatible with Brother and 3rd Party solutions¹⁹
- NFC for secure authentication





Secure by Design

To keep pace with the ever-evolving legislation on privacy and data security, our devices offer the latest industry-standard security features to securely protect your data.

All our products are secure as standard. With businesses shifting towards Zero Trust environments, we know that security is your highest priority. Our security experts continuously research new enhancements to products, solutions and services to proactively ensure all our products are 'secure by design'.

The HL-L6410DN provides a range of robust features. It uses triple-layer security at a device, network and document level which is verified through external security certification. This offers added peace of mind and guarantees that the integrity of your data is maintained at every step.





The **HL-L6410DN** comes with a flexible suite of security features and solutions that can be tailored to your business, enabling you to easily audit, control and manage your fleet of devices securely.



Your device protects your business by reducing its attack surface through:

Restricting user access - by using LDAPS or Windows Active Directory together with NFC authentication, only authorised users are able to access the device.

Restricting privileges at a device level - with Secure Function Lock and Setting Lock, only authorised users are permitted access to specific functions.

Maintaining device integrity - with runtime intrusion detection, Secure Boot, digitally signed firmware and end-to-end encrypted connections, devices are always performing at their optimum level of security.



Network Protection

Your network is protected with flexible industry standard features and management tools including:

Intrusion protection - with protocol management, interface restrictions and IPV4 filtering, you have the flexibility to adapt device settings to your business.

Secure connection - securely connect to enterprise level wired and wireless networks through industry standard IEEE 802.1X.

Secure encrypted communication - by using flexible industry standards such as TLS, SSH, IPSEC, HTTPS and SNMP3, your business can tailor the device to its network.

Easily manage and configure your security profile - using Device Master Settings, BRAdmin Pro 4 and Mass Deployment Tool, your business can apply settings to entire fleets of devices.

Audit your devices - using SIEM integration through Syslog, you can gather real time usage information on your devices.



Engineered for Performance

The HL-L6410DN Mono Laser Printer is engineered for performance with its robust design, upgraded memory, and long-life components. These are key features for ensuring consistent performance and minimising downtime so users can have confidence that their printer will keep on performing without interruption.

Model Number	Parts Life
Engine Life	600k pages
Fuser Unit	200k pages
Drum Unit	75k (Auto Reset)





As working conditions change, security is more critical than ever. That's why each single function printer and all-in-one comes equipped with a range of features that deliver enterprise level security.

To safeguard data against loss or theft, Transport Layer Security (TLS), Secure Socket Layer (SSL), IPSec and Scan to SSH Server (SFTP) are supported so that your most confidential files transfer using up to 256-bit encryption during transmission over the network. Using automatic intrusion detection, devices recognise abnormal activity and take preventative measures in order to ensure the printer remains secure.

Plus, identity management and access control help to reduce risk with selective user restriction, only allowing authorised employees or groups to get instant access to specific settings and functions they need.



Your documents are protected through encryption, storage protection and secure print solutions including:

Encrypted document transfer - when you send your print data from your computer to the device, IPPS/HTTPS encryption ensures your data is secure and unreadable.

Non-persistent internal memory - all print job data is automatically wiped during a reboot and data is purged, ensuring no information is left on the device.

Secure print release - using a Brother secure print solution, documents are only released when you are ready to print and collect them.

Optional 3rd party integration* - through Brother Solutions Interface (BSI), our devices can be fully integrated with trusted 3rd party partners such as Kofax, YSoft, and more. These add an extra layer of security to your business.

*Optional third party utilities compatible with the HL-L6410DN will require additional purchase.



Seamless Integration with Brother Solutions Interface (BSI)

Whether you already use print software or would like to understand how specialist print software can help your business, we are here to help.

As a Brother customer, you will have access to a wide choice of leading software vendors including Kofax, YSoft, and many more. We work closely with our software partners across print management and document capture to create tailored solutions for your specific requirements. When we partner with a software vendor, we ensure your HL-L6410DN works even harder to meet your needs.

Optional third party utilities compatible with the HL-L6410DN will require additional purchase.







Solutions Enabled

Unlock new possibilities with our range of Brother Pro Upgrades*

Automate workflows and improve business processes and security with print management solutions.

We offer a suite of document management, security and workflow solutions which can be added to the HL-L6410DN to provide additional professional features to further improve your business processes.





Printer Management

Remote Panel* Remote printer support

Remote Panel operates in real-time, offering a complete interactive interface to your printer. Your IT provider can access the full functionality of your printer, to quickly diagnose and resolve any issues and enable settings to be changed as if they were physically standing at the printer.

Effortlessly order your toner cartridge supplies directly from your printer, with the Order Supplies service. In one touch, your selected supplier will be notified when you require replacement supplies and arrange

Order Supplies* Order supplies from your printer

delivery, ensuring you never run out of toner when you need it.

*Brother Pro Upgrades are optional and will require additional purchase.



Request Help*

Diagnostic reports for IT administrators

automatically emailed to your IT administrator.

Request Help is a Brother service that enables your IT

administrator or service provider to easily troubleshoot errors

that may occur. You simply press the 'Request Help' icon on

the control panel and a full diagnostic report is created and





Secure Print Plus*

Print secure documents from a specific printer

Secure Print+ enables you to print your confidential business documents securely. Your sensitive documents are only printed when you are ready to collect them from the printer. Only authorised staff can collect their documents and users are easily added or removed.

Advance Secure Print* Print your document from any printer connected to your network

Pull printing is a unique way of printing wherever you are in the office. Advance Secure Print enables you to print your document from any printer connected to your network using a PIN or with a tap of an authorised NFC card. Brother Advance Secure Print works with compatible devices activated with this feature.



Barcode Print Plus* Printing barcode fonts with ease

Brother's Barcode Print+ enables you to easily print barcodes from your Brother printer. You simply supply your printer with the information for the barcode, the barcode is then printed exactly as it should appear. The quality of the barcodes reflects Brother's exceptional printing standards. So, The printed 2D and 3D barcode is easily read by a variety of barcode readers and scanners.

*Brother Pro Upgrades are optional and will require additional purchase.





General

Technology

Electrophotographic Laser

Memory

1GB

Control panel

8.9cm Colour Touchscreen LCD

Local Interface

Hi-Speed USB 2.0, USB 2.0 Host (Rear)

Wired Network

Gigabit Ethernet

Processor

Main: Cortex-A53 1.2GHz Dual Core Sub: ARM946 150MHz

Wireless Network (optional)

2.4GHz Support

Carton Contents

Device, Inbox Toners, Drum, Power Supply Cord, Quick Set-Up Guide, USB Cable

Print

Print Speed (A4)

1-Sided: 50ppm 2-Sided: 24 sides per minute

FPOT

(First Print Out Time)

Up to 6.7 Seconds Mono

Quiet Mode

A mode to reduce the printing noise

Resolution

Up to 1200 x 1200dpi

Print Languages

PCL6, BR-Script3, IBM
Proprinter XL, Epson FX-850,
PDF Version 1.7, XPS Version 1.0

Embedded Fonts (PCL)

73 Scalable fonts,12 Bitmap fonts

Embedded Barcodes (PCL)

16 barcodes*

*Code39, Interleaved 2 of 5,
FIM (US-PostNet), Post Net
(US-PostNet) EAN-8, EAN-13,
UPC-A, UPC-E, Codabar, ISBN
(EAN), ISBN (UPC-E), Code128
(set A, set B, set C), EAN128
(set A, set B, set C), Code93,
GS1Databar, MSI

Embedded Fonts (Postscript)

66 Scalable fonts

Printer Functions

N-up Printing

Reduce up to 25 pages into a single page

Poster Printing

Enlarge a single page into a poster using 2x2, 3x3, 4x4 or 5x5 pages

Toner Save Mode

Use the Toner Save Mode to reduce toner consumption without affecting print speed

Watermark Printing

Watermark your documents with predefined text, custom logo or custom messages

ID Printing

Add identification to your printed documents (date and time, short custom message or PC username)

Booklet Printing

Print documents in A5 booklet format using automatic or manual 2-sided print

Print Profiles

Store your favourite driver settings as profiles to easily recall them

Direct Print

Print directly from a USB flash memory drive. Supported formats include; PDF 1.7, JPEG, Exif+JPEG, PRN (created using printer driver of model), TIFF (scanned using brother model), XPS Version 1.0

Manual 2-Sided Print

Manual 2-sided printing (recommended for media not supported by automatic 2-sided print)

Storage Print

Easily retrieve and print your documents which are AES 256 encrypted and held within an attached USB flash memory drive storage (not included)

Reverse Print

Rotate the content of a printed document by 180°

Carbon Copy

Prints additional copies of the same document to paper taken from additional paper trays

Print Complete Notice

A printing notification can be set to go to your computer

Match Media

Assign an ID to a specific tray to make the selection of different media types from a specific tray easier

Skip Tray

Configures your paper tray selection to avoid specific trays/media for regular printing

Job Separation

Insert a different coloured piece of paper between different print jobs to separate them for easy identification

Secure Print

Protect print jobs with a 4 digit release code required at the device in order for them to be printed

Printer Driver

Windows

Windows 11 (32 and 64 bit editions) and more

macOS

Printing via macOS requires the use of AirPrint. Mac drivers are not provided.

Linux

CUPS, LPD/LPRng (i686 and x86_64)

ChromeOS

Supports native ChromeOS printing

PCL Driver

Generic PCL XL driver

PostScript Universal Printer Driver

Driver for Windows that enables you to print to any network or locally connected Brother printer

Visit www.brother.co.za/en/support for the full list of supported OS and to download the latest drivers and software.

Paper Handling¹¹

Paper Input Standard Tray

520 Sheets (with paper low detection)

Multi Purpose Tray

100 Sheets

Paper Output

250 Sheets A4 (with stack full sensor)

Envelope Printing

Yes from multi purpose tray

Media Sizes Standard Tray

A4, Letter, B5(JIS), A5, A5(Long Edge), A6, Executive, Legal, Mexico Legal, India Legal, A4 short (270mm), Folio,16K

Multi Purpose Tray

Width 69.8 to 215.9 mm, Length 127 to 355.6 mm Envelope: COM-10, DL, C5, Monarch

Auto 2-Sided

A4

Media Type and Weights Standard Tray

Plain Paper, Letterhead, Coloured Paper, Thin Paper, Recycled Paper, Thick Paper, 60-163gsm

Multi Purpose Tray

Plain Paper, Letterhead, Coloured Paper, Thin Paper, Thick Paper, Thicker Paper, Recycled Paper, Bond, Label, Envelope, Env. Thin, Env.Thick, 60-230gsm

Auto 2-Sided

Plain Paper, Letterhead, Coloured Paper, Thin Paper, Recycled Paper, 64-105gsm

Mobile and Web Connectivity

Scanning functionality is not available on single function printers. Please check your model for compatibility.

Brother Mobile Connect¹⁷ (Android)

Print from, scan to, preview copies and check the machine status from an Android device

Brother Mobile Connect¹⁷ (iPad / iPhone)

Print from, scan to, preview copies and check the machine status from an iPad/iPhone

Apple AirPrint¹⁷

Print from and scan to most common file types from any AirPrint enabled application

Brother Print Service Plugin¹⁷

Print from an Android devices without a dedicated App.

Mopria^{™ 17}

Print most common file types from Mopria™ supported Android devices

Web Connect¹⁸

Print from and scan to without using a PC on Box, Dropbox, Evernote, OneDrive, Google Drive™ OneNote

Software

Scanning functionality is not available on single function printers. Please check your model for compatibility.

Brother iPrint&Scan Desktop^{15,17}

Print from, scan to, preview copies and check the machine status from Windows or macOS PC

Utilities

Provides setup guides, manual, FAQ, troubleshooting, contact to Brother customer service, PaperPort SE 14, 16, 17 document management and sharing program from KOFAX

Easy Setup

Simple access to drivers and software for the installation of your Brother machine f support.brother.com

Fleet Management Tools

Unattended Installer¹⁶

Ability to centrally deploy and customise our drivers and software

MSI Installer16

Modular installers that can be distributed through On-premise Active Directory

BRAdmin^{16,17}

LAN/WAN management software

Embedded Web Server

Web based print management software embedded onto the device

Driver Deployment Wizard^{16,17}

Easily create print drivers for hassle free deployment over your network

Mass Deployment Tool¹⁶

Provides a configuration interface to help manage and deploy device settings

Status Monitor¹⁶

Monitor the status of your machine from your computer

Connectivity

Wired Network

Gigabit Ethernet (10Base-T/100Base-TX/1000Base-T)

Optional Wireless Network Card²²

2.4GHz: IEEE 802.11 b/g/n (Infrastructure Mode) IEEE 802.11 g/n (Wi-Fi Direct) (Optional NC-9110W)

Wi-Fi Direct®22

Print wirelessly without having to go through a wireless access point (both automatic and manual methods supported)

Wireless Setup Support²²

Wi-Fi Protected Setup (WPS)

Wireless Applications²²

Vertical Pairing

Mobile

Print from your mobile device with Brother Mobile Connect Airprint or Mopria

Local Interface

Hi-Speed USB 2.0, USB 2.0 Host (Rear)

Warranty

5-Year On-Site Warranty

When you purchase a Brother printer and our genuine inks or toners, we'll support you every step of the way with our FREE 5-year warranty commitment. YOU DO NOT NEED TO REGISTER YOUR PRODUCT, our warranty is automatic when you purchase your Brother printer. To keep your Brother machine running in optimal condition we recommend using only Brother Genuine Consumables, this will ensure you automatically enjoy our exclusive 5-year warranty.



(3rd party card readers require

additional purchase. Other card

readers supported if registered

via the embedded web server)

Near-Field Communications (NFC) / Card Reader Support*

Integrated NFC Reader

Supported NFC standards include: (ISO14443 Type A) MIFARE Standard/Plus/ Ultralight/Ultralight C/DESfire my-d move, Tag-it (ISO15693 Type B)

External NFC Card Reader Support

RFIDeas pcProx Enroll

- RDR-6081AKU
- RDR-6281AKU
- RDR-6381AKU
- RDR-6E81AKU
- RDR-6H81AKU

RFIDeas AIR ID Enroll

- RDR-7081AKU
- RDR-7581AKU
- RDR-7F81AKU

Elatec

- TWN3 MIFARE
- TWN3 MIFARE NFC
- TWN3 Multi ISO
- TWN4 MIFARE NFC

.U (U (1)

^{*} Not supplied by Brother International

Security Features

Wired Network Security

SMTP-AUTH, SSL/TLS (IPPS, HTTPS, SMTP, LDAP), SNMP v3 802.1x (EAP-MD5, EAP-FAST, PEAP, EAP-TLS, EAP-TTLS), Kerberos, IPsec

Wireless Network Security²²

WEP 64/128 bit, WPA-PSK (TKIP/AES), WPA2-PSK (TKIP/AES), WPA3-SAE (AES) *Wi-Fi Direct supports WPA2-PSK (AES) only. SMTP-AUTH, SSL/TLS (IPPS, HTTPS, SMTP, LDAP), SNMP v3, 802.1x (EAP-MD5, EAP-FAST, PEAP, EAP-TLS, EAP-TTLS), Kerberos, IPsec

IPv4

ARP, RARP, BOOTP, DHCP, APIPA(Auto IP), WINS/NetBIOS name resolution, DNS Resolver, mDNS, LLMNR responder, LPR/LPD, Custom Raw Port/Port9100, SMTP Client, IPP/IPPS, FTP Client and Server, CIFS Client, TELNET Server, SNMPv1/v2c/v3, HTTP/HTTPS server, TFTP client and server, ICMP, Web Services (Print/Scan), SNTP Client, LDAP, Syslog

IPv6

NDP, RA, DNS resolver, mDNS, LLMNR responder, LPR/LPD, Custom Raw Port/Port9100, IPP/IPPS, SMTP Client, FTP Client and Server, CIFS Client, TELNET Server, SNMPv1/v2c/v3, HTTP/HTTPS server, TFTP client and server, ICMPv6, SNTP Client, LDAP, Web Services (Print/Scan), Syslog

IP Filter

Restrict which network users can or cannot access the device over the network (IPv4 only)

Secure Print

Protect print jobs with a 4 digit release code required at the device in order for them to be printed

E-mail Notifications

Automatically have the device send e-mail alerts when it requires attention, such as when the toner is low or needs replacing

E-mail Reports

Receive usage reports on a regular basis via e-mail

Automatic Intrusion Detection

All Brother Print devices are secure by design. Devices automatically recognise security attacks and take preventative measures, including rebooting where necessary, to ensure the device remains secure

Firmware Updates

In addition to allowing automatic update alerts to install the latest version the printer can be set to not receive older firmware versions to avoid downgrade by an unauthorised user

Cloud Secure Print

Enables password protected driverless print job release

Setting Lock

Secures access to the devices control panel by locking it

Certificate Management

Use the default standard self-signed, create a custom self-signed certificate, certificate signing request (CSR), or external public cerificate & private key for protected network communication

Secure Function Lock 3.0

Use a 4 digit pin or a password to identify and authenticate an individual or groups of users over a network. Allows access control for up to 200 users

Digitally-signed Firmware

The firmware for Brother print and scan devices is digitally signed and secure

Syslog

Allows IT Admin to access a single application (SIEM tool) to get device status updates for audit purposes over Syslog

On-Premise Active Directory/LDAP Authentication

Utilise existing infrastructure to restrict access to Brother devices using AD/LDAP.
Staff can easily use their existing network login credentials to authenticate

Port-based Network Access Control

(IEEE 802.1x)
Brother devices are in full compliance with this standard, to allow connection to an 802.1x EAP (Extensible Authentication Protocol) protected network

Restrict network protocols

The Protocol Control feature allows an administrator to restrict communication protocols (e.g. FTP, Telnet) as required

Store Print Log

Allows audit of a print log file saved to CIFS server. Record ID, type, name, user, date, time, page count for every print job

Supplies and Consumables

Inbox Toner⁷

1 x 25,000 pages (BK)

Standard Yield Toner⁷

TN3607 - 3,000 pages

Super High Yield Toner⁷

TN3607XXL - 11,000 pages

Max Capacity Yield Toner⁷

TN3617XL - 25,000 pages

Drum Unit

DR3607 Approx 75,000 pages at 3 pages per job

Optional Accessories

Paper Trays

520 sheet tray LT-6505 4 x 520 sheet tower tray TT-4000

Maximum combinations 2 x LT-6505 or TT-4000

Wi-Fi Module

NC-9110W

Optional wireless network interface

Solutions and Upgrades¹⁹

Brother Pro Upgrades*

Order Supplies, Remote Panel, Request Help, SecurePrint+, Advance Secure Print and Barcode Print+

*Brother Pro Upgrades are optional and will require additional costs.

3rd Party Compatibility*

Brother Solutions Interface (BSI)

Create powerful cloud and on-premise solutions directly integrating the advanced print, scan and security capabilities of Brother devices.

For more information contact

Brother International South Africa

3rd Party Solutions

Compatible through Brother Solutions Interface (BSI) including Kofax ControlSuite, YSoft and more.

*Optional third party utilities compatible with the HL-L6410DN will require additional costs.

Duty Cycle

Recommended Monthly

Up to 16,000 pages

Dimensions and Weights

With Carton (WxDxH)

497 x 494 x 422mm - 15.90kg

Without Carton (WxDxH)

402 x 396 x 319mm - 13.50kg

Operating Requirement

Power Requirement

220-240V AC 50/60Hz

Operating Environment

Humidity 20 - 80 % 10°C - 32.5°C 50°F - 90.5°F

Storage Environment

Humidity 35 - 85 % 0°C - 40°C 32°F - 104°F

Environment

Approx Power Consumption^{13,23}

Printing: 710W

Printing in quiet mode: 430W

Ready: 31W Sleep: 5.9W Power Off: 0.05W

TEC Value

0.63 kWh/week

Sound Power¹²

Printing: 7.07B(A) Ready: 4.90B(A) Quiet Mode: 6.54B(A) Deep Sleep: Inaudible

Sound Pressure¹²

PC Printing (Mono): Approx. 54.0dB(A) Ready: 35.0db(A) Quiet Mode: 50.0db(A)

Toner Save

This reduces the toner consumption to get more pages from your consumables

- Approx. declared yield value in accordance with ISO/IEC 19752
- Capacity calculated with 80gsm paper 11
- Sound pressure and sound power level in accordance with ISO 7779 12
- 13 Power consumption power off is measured according to IEC 62301 Edition 2.0
- Windows and macOS only 15
- 16 Windows only
- 17 Optional download
- 18 Requires an internet connection
- Requires additional activation and subject to additional costs 19
- Optional Wireless Network Card (NC-9110W) 22
- 23 Power consumption is measured using ENERGY STAR Ver 3.1 test method network configuration











96 Sovereign Drive, Route 21 Corporate Park, Irene Tel 0861 brother Email info@brother.co.za www.brother.co.za https://support.brother.com/











